

Voice Technologies connector wiring			2011			
Brand	TYP	Connector	VT100	VT400	VT401/401HS	VT402
			<b>3-wire</b>	<b>3-wire</b>	<b>3-wire</b>	<b>3-wire</b>
<b>AKG</b>	WMS60, WMS61 WMS80, WMS81	TA3F	Pin1: Ground(green) Pin2: NF (copper) Pin3: +VDC(red) Pin1 to Pin2 10KOhm	Pin1: ground(green) Pin2: NF (Copper) Pin3: +VDC (red)	Pin1: Ground(Green) Pin2: NF/VDC(Copper) Pin3: 12kOhm to Pin2	Pin1: ground(green) Pin2: NF (Copper) Pin3: +VDC (red)
<b>Audio-Technica</b>	ATW-27/T31/T35 T27/T15/T51/T75	Hirose HR10-7P-4S	Pin1:ground(grren) Pin3: NF (copper) Pin4: +VDC (red) Pin1 to Pin3 10KOhm	Pin1:ground(green) Pin2: Aux-In --- Pin3: NF (Copper) Pin4: +VDC (red)	Pin1:Ground(Green) Pin2: Aux-In --- Pin3: NF/VDC(Copper) Pin4: 12KOhm to Pin3	Pin1:Ground(green) Pin2: Aux-In --- Pin3: NF (Copper) Pin4: +VDC (red)
<b>Audio Limited</b>	TX-2000 RMS-2000-mxl	Lemo 6 Pin	Pin1: NF(copper) Pin2: +VDC(red) Pin5: Ground(green) Pin3 to 4 bridged Pin1 to Pin5 10KOhm	Pin1: NF(Copper) Pin2: +VDC(red) Pin5: Ground(green) Pin3to4 bridged	Pin1: NF/VDC(Copper) Pin2: 12KOhm to Pin1 Pin5: Ground(Green) Pin3to4 bridged	Pin1: NF(Copper) Pin2: +VDC(red) Pin5: Ground(green) Pin3to4 bridged
<b>MiPro</b>	alte Serie	4-Pin plug	Pin1: Ground (green) Pin2: bridget to Pin1 Pin3: NF (copper) Pin4: +VDC (red) Pin1 to Pin3 10KOhm	Pin1: Ground (green) Pin2: bridget to Pin1 Pin3: NF (copper) Pin4: +VDC (red)	Pin1: Ground (Green) Pin2: bridget to Pin1 Pin3: NF/VDC(Copper) Pin4: 12KOhm to Pin3	Pin1: Ground (green) Pin2: bridget to Pin1 Pin3: NF (copper) Pin4: +VDC (red)
<b>MiPro</b>	neue Serie	TA4F	Pin1: Ground(green) Pin2: Jumper to Pin1 Pin3: NF(Copper) Pin4: +VDC(red) Pin1 to Pin3 10 Kohm	Pin1: Ground(green) Pin2: Jumper to Pin1 Pin3: NF(Copper) Pin4: +VDC(red)	Pin1: Ground(Green) Pin2: Jumper to Pin1 Pin3: NF/VDC(Copper) Pin4: 12KOhm to Pin3	Pin1: Ground(green) Pin2: Jumper to Pin1 Pin3: NF(Copper) Pin4: +VDC(red)
<b>Sennheiser</b>	Evolution 2 Serie	3,5mm Jack	Tip : +VDC(red) Sleeve : NF&Ground (Copper&Green)	Tip : +VDC(red) Sleeve : NF&Ground (Copper&Green)	Tip : Copper Sleeve : Ground (green)	Tip : +VDC(red) Sleeve : NF&Ground (Copper&Green)
<b>Shure</b>	L-11, SC1, LX1 U-1, T-1, UC-1 L-1, UT-1, UR-1	TA4F	Pin1: Ground(copper) Pin2: +VDC (red) Pin3: NF (withte) Pin1 to Pin3 10KOhm	Pin1: Ground(green) Pin2: +VDC (red) Pin3: NF (copper) Pin4: ----	Pin1: Ground(Green) Pin2: 12KOhm to Pin3 Pin3: NF/VDC(Copper) Pin4: ----	Pin1: Ground(green) Pin2: +VDC (red) Pin3: NF (copper) Pin4: ----
<b>Shure</b>	U1L-VA UC1L	Lemo 4-Pin	Pin1: NF(Copper) Pin2: +VDC(red) Pin3: bridget to Pin1 Pin4: Ground(green) Pin1 to Pin4 10KOhm	Pin1: NF(Copper) Pin2: +VDC(red) Pin3: bridget to Pin1 Pin4: Ground(green)	Pin1: NF/VDC(Copper) Pin2: 12KOhm to Pin1 Pin3: bridget to Pin1 Pin4: Ground(Green)	Pin1: NF(Copper) Pin2: +VDC(red) Pin3: bridget to Pin1 Pin4: Ground(green)
<b>Trantec</b>	S4.5 , S4000	Lemo 4 Pin	Pin1: ground(green) Pin2: +VDC(red) Pin4: NF(Copper) Pin1 to Pin4 10KOhm	Pin1: ground(green) Pin2: +VDC(red) Pin3: ---- Pin4: NF(Copper)	Pin1: ground(Green) Pin2: 12KOhm to Pin4 Pin3: ---- Pin4: NF/VDC(Copper)	Pin1: ground(green) Pin2: +VDC(red) Pin3: ---- Pin4: NF(Copper)

Brand	TYP	Connector	VT500H/VT500W	VT500B	VT506B	VT506H/VT506W
			<b>3-wire</b>	<b>3-wire</b>	<b>3-wire</b>	<b>3-wire</b>
<b>AKG</b>	WMS60, WMS61 WMS80, WMS81	TA3F	Pin1: ground(Copper) Pin2: NF (green) Pin3: +VDC (red)	Pin1: ground(green) Pin2: NF (Copper) Pin3: +VDC (red)	Pin1:ground (green) Pin2: NF (Copper) Pin3: +VDC (red)	Pin1: ground(Copper) Pin2: NF (green) Pin3: +VDC (red)
<b>Audio-Technica</b>	ATW-27/T31/T35 T27/T15/T51/T75	Hirose HR10- 7P-4S	Pin1:Ground(Copper) Pin2: Aux-In --- Pin3: NF (Green) Pin4: +VDC (red)	Pin1:Ground(green) Pin2: Aux-In --- Pin3: NF (Copper) Pin4: +VDC (red)	Pin1:Ground(green) Pin2: Aux-In --- Pin3: NF (Copper) Pin4: +VDC (red)	Pin1:Ground(Copper) Pin2: Aux-In --- Pin3: NF (Green) Pin4: +VDC (red)
<b>Audio Limited</b>	TX-2000 RMS-2000-mxl	Lemo 6 Pin	Pin1: NF(Green) Pin2: +VDC(red) Pin5: Ground(Copper) Pin3 to 4 bridged	Pin1: NF(Copper) Pin2: +VDC(red) Pin5: Ground(green) Pin 3 to 4 bridged	Pin1: NF(Copper) Pin2: +VDC(red) Pin5: Ground(green) Pin3 to 4 bridged	Pin1: NF(Green) Pin2: +VDC(red) Pin5: Ground(Copper) Pin3 to 4 bridged
<b>MiPro</b>	alte Serie	4-Pin plug	Pin1: Ground (Copper) Pin2: bridget to Pin1 Pin3: NF (Green) Pin4: +VDC (red)	Pin1: Ground (green) Pin2: bridget to Pin1 Pin3: NF (copper) Pin4: +VDC (red)	Pin1: Ground (green) Pin2: bridget to Pin1 Pin3: NF (copper) Pin4: +VDC (red)	Pin1: Ground (Copper) Pin2: bridget to Pin1 Pin3: NF (Green) Pin4: +VDC (red)
<b>MiPro</b>	neue Serie	TA4F	Pin1: Ground(Copper) Pin2: Jumper to Pin1 Pin3: NF(green) Pin4: +VDC(red)	Pin1: Ground(green) Pin2: Jumper to Pin1 Pin3: NF(Copper) Pin4: +VDC(red)	Pin1: Ground(green) Pin2: Jumper to Pin1 Pin3: NF(Copper) Pin4: +VDC(red)	Pin1: Ground(Copper) Pin2: Jumper to Pin1 Pin3: NF(Green) Pin4: +VDC(red)
<b>Sennheiser</b>	Evolution 2 Serie	3,5mm Jack	Tip : +VDC(red) Sleeve : NF&Ground (Copper&Green)	Tip : +VDC(red) Sleeve : NF&Ground (Copper&Green)	Tip : +VDC(red) Sleeve : NF&Ground (Copper&Green)	Tip : +VDC(red) Sleeve : NF&Ground (Copper&Green)
<b>Shure</b>	L-11, SC1, LX1 U-1, T-1, UC-1 L-1, UT-1, UR-1	TA4F	Pin1: Ground(Copper) Pin2: +VDC (red) Pin3: NF (Green) Pin4: ----	Pin1: Ground(green) Pin2: +VDC (red) Pin3: NF (copper) Pin4: ----	Pin1: Ground(green) Pin2: +VDC (red) Pin3: NF (copper) Pin4: ----	Pin1: Ground(Copper) Pin2: +VDC (red) Pin3: NF (Green) Pin4: ----
<b>Shure</b>	U1L-VA UC1L	Lemo 4-Pin	Pin1: NF(Green) Pin2: +VDC(red) Pin3: bridget to Pin1 Pin4: Ground(Copper)	Pin1: NF(Copper) Pin2: +VDC(red) Pin3: bridged to Pin1 Pin4: Ground(green)	Pin1: NF(Copper) Pin2: +VDC(red) Pin3: bridged to Pin1 Pin4: Ground(green)	Pin1: NF(Green) Pin2: +VDC(red) Pin3: bridget to Pin1 Pin4: Ground(Copper)
<b>Trantec</b>	S4.5 , S4000	Lemo 4 Pin	Pin1: ground(Copper) Pin2: +VDC(red) Pin3: ---- Pin4: NF(green)	Pin1: ground(green) Pin2: +VDC(red) Pin3: ---- Pin4: NF(Copper)	Pin1: ground(green) Pin2: +VDC(red) Pin3: ---- Pin4: NF(Copper)	Pin1: ground(Copper) Pin2: +VDC(red) Pin3: ---- Pin4: NF(Green)

Brand	TYP	Connector	VT701	VT702	VT710	VT720	VT760
			<b>3-wire</b>	<b>3-wire</b>	<b>3-wire</b>	<b>3-wire</b>	<b>3-wire</b>
<b>AKG</b>	WMS60, WMS61 WMS80, WMS81	TA3F	Pin1: Ground(Copper) Pin2: NF/VDC(red) Pin3: 15kOhm to Pin2	Pin1: Ground(Copper) Pin2: NF/VDC(red) Pin3: 1.5kOhm to Pin2	Pin1: ground (silver) Pin2: NF (withe) Pin3: +VDC (red)	Pin1: ground (silver) Pin2: NF (withe) Pin3: +VDC (red)	Pin1: ground (copper) Pin2: NF (withe) Pin3: +VDC (red)
<b>Audio-Technica</b>	ATW-27/T31/T35 T27/T15/T51/T75	Hirose HR10-7P-4S	Pin1:Ground(Copper) Pin2: Aux-In --- Pin3: NF/VDC(red) Pin4: 15kOhm to Pin3	Pin1:Ground(Copper) Pin2: Aux-In --- Pin3: NF/VDC(red) Pin4: 1.5kOhm to Pin3	Pin1:Ground(Silver) Pin2: Aux-In --- Pin3: NF (withe) Pin4: +VDC (red)	Pin1:ground(Silver) Pin2: Aux-In --- Pin3: NF (withe) Pin4: +VDC (red)	Pin1:ground(Copper) Pin2: Aux-In --- Pin3: NF (withe) Pin4: +VDC (red)
<b>Audio Limited</b>	TX-2000 RMS-2000-mxl	Lemo 6 Pin	Pin1: NF/VDC(red) Pin2: 15kOhm to Pin1 Pin5: Ground(copper) Pin3 to 4 bridged	Pin1: NF/VDC(red) Pin2: 1.5kOhm to Pin1 Pin5: Ground(copper) Pin3 to 4 bridged	Pin1: NF(withe) Pin2: +VDC(red) Pin5: Ground(silver) Pin3 to 4 bridged	Pin1: NF(withe) Pin2: +VDC(red) Pin5: Ground(Silver) Pin3 to 4 bridged	Pin1: NF(withe) Pin2: +VDC(red) Pin5: Ground(Copper) Pin3 to 4 bridged
<b>MiPro</b>	alte Serie	4-Pin plug	Pin1: Ground (copper) Pin2: bridget to Pin1 Pin3: NF/VDC(red) Pin4: 15kOhm to Pin3	Pin1: Ground (copper) Pin2: bridget to Pin1 Pin3: NF/VDC(red) Pin4: 1.5kOhm to Pin3	Pin1: Ground (silver) Pin2: bridget to Pin1 Pin3: NF (withe) Pin4: +VDC (red)	Pin1: Ground (silver) Pin2: bridget to Pin1 Pin3: NF (withe) Pin4: +VDC (red)	Pin1: Ground (Copper) Pin2: bridget to Pin1 Pin3: NF (withe) Pin4: +VDC (red)
<b>MiPro</b>	neue Serie	TA4F	Pin1: Ground(Copper) Pin2: Jumper to Pin1 Pin3: NF/VDC(red) Pin4: 15kOhm to Pin3	Pin1: Ground(Copper) Pin2: Jumper to Pin1 Pin3: NF/VDC(red) Pin4: 1.5kOhm to Pin3	Pin1: Ground(Copper) Pin2: Jumper to Pin1 Pin3: NF(Withe) Pin4: +VDC(red)	Pin1: Ground(Silver) Pin2: Jumper to Pin1 Pin3: NF(Withe) Pin4: +VDC(red)	Pin1: Ground(Copper) Pin2: Jumper to Pin1 Pin3: NF(Withe) Pin4: +VDC(red)
<b>Sennheiser</b>	Evolution 2 Serie	3,5mm Jack	Tip: (red) Sleeve : ground(copper)	Tip: (red) Sleeve : ground(copper)	Tip : +VDC(red) Sleeve : NF&Ground (withe & Copper)	Tip : +VDC(red) Sleeve : NF&Ground (withe & silver)	Tip : +VDC(red) Sleeve : NF&Ground (withe & Copper)
<b>Shure</b>	L-11, SC1, LX1 U-1, T-1, UC-1 L-1, UT-1, UR-1	TA4F	Pin1: Ground(copper) Pin2: 15kOhm to Pin3 Pin3: NF/VDC(red) Pin4: ----	Pin1: Ground(copper) Pin2: 1.5kOhm to Pin3 Pin3: NF/VDC(red) Pin4: ----	Pin1: Ground(silver) Pin2: +VDC (red) Pin3: NF (withe) Pin4: ----	Pin1: Ground(silver) Pin2: +VDC (red) Pin3: NF (withe) Pin4: ----	Pin1: Ground(Copper) Pin2: +VDC (red) Pin3: NF (withe) Pin4: ----
<b>Shure</b>	U1L-VA UC1L	Lemo 4-Pin	Pin1: NF/VDC(red) Pin2: 15kOhm to Pin1 Pin3: bridget to Pin1 Pin4: Ground(Copper)	Pin1: NF/VDC(red) Pin2: 1.5kOhm to Pin1 Pin3: bridget to Pin1 Pin4: Ground(Copper)	Pin1: NF(withe) Pin2: +VDC(red) Pin3: bridget to Pin1 Pin4: Ground(silver)	Pin1: NF(withe) Pin2: +VDC(red) Pin3: bridget to Pin1 Pin4: Ground(silver)	Pin1: NF(withe) Pin2: +VDC(red) Pin3: bridget to Pin1 Pin4: Ground(Copper)
<b>Trantec</b>	S4.5, S4000	Lemo 4 Pin	Pin1: ground(Copper) Pin2: 15kOhm to Pin4 Pin3: ---- Pin4: NF/VDC(red)	Pin1: ground(Copper) Pin2: 1.5kOhm to Pin4 Pin3: ---- Pin4: NF/VDC(red)	Pin1: ground(silver) Pin2: +VDC(red) Pin3: ---- Pin4: NF(withe)	Pin1: ground(silver) Pin2: +VDC(red) Pin3: ---- Pin4: NF(withe)	Pin1: ground(Copper) Pin2: +VDC(red) Pin3: ---- Pin4: NF(withe)

Brand	TYP	Connector	VT800B/VT800H	VT801B/VT801H	VT900	VT910
			<b>3-wire</b>	<b>3-wire</b>	<b>3-wire</b>	<b>3-wire</b>
<b>AKG</b>	WMS60, WMS61 WMS80, WMS81	TA3F	Pin1: ground (copper) Pin2: NF (transp.) Pin3: +VDC (red)	Pin1: ground (copper) Pin2: NF (transp.) Pin3: +VDC (red)	coming soon blue - NF/+VDC Copper - Ground	coming soon blue - NF/+VDC Copper - Ground
<b>Audio-Technica</b>	ATW-27/T31/T35 T27/T15/T51/T75	Hirose HR10-7P-4S	Pin1:ground(Copper) Pin2: Aux-In --- Pin3: NF (transp.) Pin4: +VDC (red)	Pin1:ground(Copper) Pin2: Aux-In --- Pin3: NF (transp.) Pin4: +VDC (red)	Pin1:ground(Copper) Pin2: Aux-In --- Pin3: NF/VDC (blue) Pin4: 1kOhm res.to Pin3	Pin1:ground(Copper) Pin2: Aux-In --- Pin3: NF/VDC (blue) Pin4: 1kOhm res.to Pin3
<b>Audio Limited</b>	TX-2000 RMS-2000-mxl	Lemo 6 Pin	Pin1: NF(transp.) Pin2: +VDC(red) Pin5: Ground(Copper) Pin3 to 4 bridged	Pin1: NF(transp.) Pin2: +VDC(red) Pin5: Ground(Copper) Pin3 to 4 bridged	Pin1: NF/VDC(blue) Pin2:1kOhm res.toPin1 Pin5: Ground(Copper) Pin3 to 4 bridged	Pin1: NF/VDC(blue) Pin2:1kOhm res.toPin1 Pin5: Ground(Copper) Pin3 to 4 bridged
<b>MiPro</b>	alte Serie	4-Pin plug	Pin1: Ground (Copper) Pin2: bridget to Pin1 Pin3: NF (transp.) Pin4 : +VDC (red)	Pin1: Ground (Copper) Pin2: bridget to Pin1 Pin3: NF (transp.) Pin4: +VDC (red)	Pin1: Ground (Copper) Pin2: bridget to Pin1 Pin3: NF/VDC (blue) Pin4: 1kOhm res.to Pin3	Pin1: Ground (Copper) Pin2: bridget to Pin1 Pin3: NF/VDC (blue) Pin4: 1kOhm res.to Pin3
<b>MiPro</b>	neue Serie	TA4F	Pin1: Ground(Copper) Pin2: Jumper to Pin1 Pin3: NF(transp.) Pin4: +VDC(red)	Pin1: Ground(Copper) Pin2: Jumper to Pin1 Pin3: NF(transp.) Pin4: +VDC(red)	Pin1: Ground(Copper) Pin2: Jumper to Pin1 Pin3: NF/VDC(blue) Pin4: 1kOhm res.to Pin3	Pin1: Ground(Copper) Pin2: Jumper to Pin1 Pin3: NF/VDC(blue) Pin4: 1kOhm res.to Pin3
<b>Sennheiser</b>	Evolution 2 Serie	3,5mm Jack	Tip : +VDC(red) Sleeve : NF&Ground (transp. & Copper)	Tip : +VDC(red) Sleeve : NF&Ground (transp. & Copper)	Tip : +VDC(blue) Sleeve : Ground(copper)	Tip : +VDC(blue) Sleeve : Ground(copper)
<b>Shure</b>	L-11, SC1, LX1 U-1, T-1, UC-1 L-1, UT-1, UR-1	TA4F	Pin1: Ground(Copper) Pin2: +VDC (red) Pin3: NF (transp.) Pin4: ----	Pin1: Ground(Copper) Pin2: +VDC (red) Pin3: NF (transp.) Pin4: ----	Pin1 : Ground Pin3 : Blue(NF/VDC) 1 kOhm Resistor Pin2 to Pin3	Pin1 : Ground Pin3 : Blue(NF/VDC) 1 kOhm Resistor Pin2 to Pin3
<b>Shure</b>	U1L-VA UC1L	Lemo 4-Pin	Pin1: NF(transp.) Pin2: +VDC(red) Pin3: bridget to Pin1 Pin4: Ground(Copper)	Pin1: NF(transp.) Pin2: +VDC(red) Pin3: bridget to Pin1 Pin4: Ground(Copper)	Pin1: NF/VDC(blue) Pin2: 1kOhm res.to Pin1 Pin3: bridget to Pin1 Pin4: Ground(Copper)	Pin1: NF/VDC(blue) Pin2: 1kOhm res.to Pin1 Pin3: bridget to Pin1 Pin4: Ground(Copper)
<b>Trantec</b>	S4.5 , S4000	Lemo 4 Pin	Pin1: ground(Copper) Pin2: +VDC(red) Pin3: ---- Pin4: NF(transp.)	Pin1: ground(Copper) Pin2: +VDC(red) Pin3: ---- Pin4: NF(transp.)	Pin1: Ground 1kOhm res. pin2 to Pin4 Pin3 : --- Pin4 : Blue(NF/VDC)	Pin1: Ground 1kOhm res. pin2 to Pin4 Pin3 : --- Pin4 : Blue(NF/VDC)